

KODIAK GENERATORS

KODIAK KD SERIES GENERATORS ARE DESIGNED FOR CONSTRUCTION JOBSITES OR INDUSTRIAL APPLICATIONS. DESIGNED TO BE DURABLE, DEPENDABLE AND PROVIDE STABLE POWER WHEN REQUIRED.

- Honda OHV with Oil Alert
- Circuit Breaker
- Full Frame Protection
- Automatic Voltage Regulator (AVR) - System allows finer voltage control for steady output and less fluctuations.
- Large Capacity Fuel Tank with Fuel Gauge - Offers greater run-time between refueling and displays current fuel level.
- GFCI Receptacles (120V, 20A T-Slot) - Construction site approved.
- Automatic Idle Control - Lowers engine speed when power is not required. Better fuel efficiency and reduces noise. Available on KD5500VR or KD7000VR(S)
- Silent Muffler with built in Spark Arrestor - For quieter, safe operation.
- Wheel Kit - Includes premium 10" pneumatic wheels, overall easier for portability (KD5500VR or KD7000VR(S) only).



Powered by
HONDA
ENGINES

	KD3000VR	KD5500VR	KD7000VR	KD7000VRS
Rated Output	2400W (3000W)	4800W (5000W)	6000W (7000W)	
Generator Type	AVR			
Engine Model	GX160	GX340	GX390	
Starting System	Recoil			Recoil/ Electric Start
AC Output	120V	120V/240V		
Rated Amps	20.0A	40.0A/20.0A	50.0A/25.0A	
Tank Capacity	16L	25L		
Running Time (Rated Load, 1/2 Load)	12.1 hrs	8.5 hrs	7.6 hrs	
Noise (dB)	75	78	79	
Dimensions (in)	23.6 x 18.5 x 19.7	27.2 x 22.8 x 21.1		
Dry Weight	102lbs	171lbs	179lbs	185lbs

**Electric Start Model KD7000VRS - Battery NOT Included.

Wheel Kit
Included with:

- KD5500VR
- KD7000VR
- KD7000VRS



MADE IN JAPAN